

MLLG-X-EMBUFO-25

25 Watt Emergency Driver

Project Name _____



DETAILS

Emergency driver designed to install with existing UFO LED High Bay to convert your LED High Bay into an emergency back up ready unit. This unit is designed to work on existing LED Fixtures up to 200 Watts. Fixture must be dimmable - either 0-10V or 1-10V. Constant output power and self testing. Works with or without 0-10V dimmers, wall switches and motion sensors. Provides to 90 minutes of emergency lighting, recharge time is 24 hours.

OVERVIEW

SKU MLLG-X-EMBUFO-25

Watts 25

Lumens

Lumens Per Watt (Efficacy) 0

Color Temperature

Voltage 100V-277V | 347V

PRODUCT DIMENSIONS

Product Dimensions 5.5 in D X 6.8 in H

Product Weight 3.96 lbs

AMP DRAW

Watts	Current Amp Draw			
	120V	240V	277V	480V
25	0.21	0.10	0.09	0.05



Product design upgrades may result in specification changes without notice. Speak to a Product Specialist for the latest information.

www.ledlightingsupply.com (888) 423-3191

Headquartered at: 1 Chestnut Street, 4M Nashua NH 03060

WebID: 2483

MLLG-X-EMBUFO-25

25 Watt Emergency Driver

Project Name _____



PRODUCT SPECIFICATIONS